

KoamTac KDC100 Rev2.83 Release Note

July 29, 2009

WARNING: DO NOT REMOVE KDC100 from PC during FW UPDATE PROCESS until AFTER resetting the KDC100 unit as outlined below.

1. Plug KDC100 into PC USB port
2. Check the KoamTac Data Collector COM port
 - Control Panel -> System -> Hardware -> Device Manager -> Ports
3. Execute **KDC200_V183.exe for yellow OLED**, **KDC100_V283.exe for blue OLED**.
4. Click Step1 Select Serial Port and select the correct COM port
 - KDC100_V183(V283) program will search available COM ports and could take few minutes to search all available COM ports. DO NOT TOUCH PC during the COM port searching.
5. Click Step2 Check KDC100
6. Click Step3 Download new F/W.
7. Reset KDC100
 - Plug KDC100 swing out USB connector (Type A) to PC USB port.
 - Press lower menu button and scan button together for 5 seconds.
 - Release lower menu button and scan button once LED becomes yellow.
 - Initial screen ("KoamTac Data Collector KDC100") is displayed once reset.
 - KDC100 stores collected data into flash memory and wouldn't lose the data during reset process. However, KDC100 options would be reset to the factory default settings.
 - Press two side buttons
 - **Go to System > Fac. Default; Select Yes & Exit; Exit Menu**
 - **Go to System > Reset Memory; Select Yes & Exit; Exit Menu**



KoamTac, Inc.

support@koamtac.com